



Overview

Model Name	APC SMART-UPS RC 1000VA 230V INDIA Harsh Environment
Includes	Smart UPS signalling RS-232 cable , USB cable , User Manual , Warranty card
Standard Lead Time	Usually in Stock
Product Distribution	India

Output

Output Power Capacity	800 Watts / 1000 VA
Max Configurable Power (Watts)	800 Watts / 1000 VA
Nominal Output Voltage	230V
Output Voltage Distortion	Less than 2%
Output Frequency (sync to mains)	50/60Hz +/- 3 Hz
Other Output Voltages	220, 240V
Crest Factor	3 : 1
Crest Factor	Double Conversion Online
Waveform Type	Sine wave
Output Connections	(4) India 3-pin 6A (Battery Backup)
Bypass	Built-in Bypass

Input

Nominal Input Voltage	230V
Input Frequency	40 - 70 Hz
Input Connections	India 3-pin 6A
Cord Length	1.52 meters
Input voltage range for main operations	100 - 280 (half load) V
Maximum Input Current	0 A
Input Breaker Capacity	10 A

Batteries & Runtime

Battery Type	Maintenance-free sealed Lead-Acid battery with suspended electrolyte : leakproof
Included Battery Modules	0

Battery Slots Empty	0
Typical recharge time	6 hour(s)
RBC Quantity	0

Communications & Management

Interface Port(s)	DB-9 RS-232 , Smart-Slot
Available SmartSlot™ Interface Quantity	0
Control panel	LED status display with On Line : On Battery : Replace Battery and Overload indicators
Audible Alarm	Alarm when on battery : distinctive low battery alarm : overload continuous tone alarm

Physical

Maximum Height	220.0 mm
Maximum Width	145.0 mm
Maximum Depth	400.0 mm
Rack Height	0 U
Net Weight	13.5 kg
Shipping Weight	14.5 kg
Shipping Height	340.0 mm
Shipping Width	235.0 mm
Shipping Depth	478.0 mm
Master Carton Units	0.0
Master Carton Weight	0.0 lbs
Color	Black
Units per Pallet	50.0
Pallet Weight	765.0 kg

Environmental

Operating Environment	0 - 40 °C
Operating Relative Humidity	0 - 95 %
Operating Elevation	0-900 meters
Storage Temperature	-20 - 60 °C
Storage Relative Humidity	0 - 95 %
Storage Elevation	0-4500 meters
Audible noise at 1 meter from surface of unit	0.000 dB

Conformance

Standard warranty	2 years repair or replace
-------------------	---------------------------